



## AD - 12 UHF Passive Antenna Divider / Combiner



- The AD-12 can either divide a UHF signal into two signal outputs or combine two signals into one signal output. Simultaneously, it provides bias voltage to boosters in post stage.
- The AD-12 utilizes an isolated grounding design that eliminates current noise due to ground loop issues with multi-receiver operation.

### Specifications

Bandwidth	UHF 600~1000MHz
Attenuation	3.5dB ( typ. )
Isolation	20dB ( typ. )
Impedance	50Ω
Max Volt/Current	50VDC/1.5A
Connector	TNC× 3
Dimensions	90.3(W)x25(H)x55.4(D)mm / 3.5(W)x1(H)x2.2(D)"
Weight	105g / 3.7oz.

